RENESAS

HD74LS190

Synchronous Up / Down Decade Counter (signal clock line)

REJ03D0452-0200 Rev.2.00 Jul.15.2005

Synchronous operation is provided by having all flip-flops clocked simultaneously so that the outputs change coincident with each other when so instructed by the steering logic. This mode of operation eliminates the output counting spikes normally associated with asynchronous (ripple clock) counters.

The outputs of the four master-slave flip-flops are triggered on a low-to-high-level transition of the clock input if the enable input is low. A high at the enable input inhibits counting. Level changes at the enable input should be made only when the clock input is high. The direction of the count is determined by the level of the down / up input. When low, the counter counts up and when high, it counts down. Level changes at the down / up input should be made only when the clock input is high. This counter is fully programmable; that is, the outputs may be preset to either level by placing a low on the load input and entering the desired data at the data inputs. The output will change to agree with the data inputs independently of the level of the clock input. This feature allows the counters to be used as modulo-N dividers by simply modifying the count length with the preset inputs. The clock, down / up, and load inputs are buffered to lower the drive requirement which significantly reduces the number of clock drivers, etc., required for long parallel words.

Two outputs have been made available to perform the cascading function: ripple clock and maximum / minimum count. The latter output produces a high-level output pulse with a duration approximately equal to one complete cycles to the clock when the counter overflows or underflows. The ripple clock output produces a low-level output pulse equal in width to the low-level portion of the clock input when an overflow or underflow conditions exists.

The counters can be easily cascaded by feeding the ripple clock output to the enable input of the succeeding counter if parallel clocking is used, or to the clock input if parallel enabling is used. The maximum / minimum count output can be used to accomplish look-ahead for high-speed operation.

Features

• Ordering Information

Part Name	Package Type	Package Code (Previous Code)	Package Abbreviation	Taping Abbreviation (Quantity)
HD74LS190P	DILP-16 pin	PRDP0016AE-B (DP-16FV)	Р	—
HD74LS190FPEL	SOP-16 pin (JEITA)	PRSP0016DH-B (FP-16DAV)	FP	EL (2,000 pcs/reel)

Notes: Please consult the sales office for the above package availability.



Pin Arrangement





Block Diagram



Absolute Maximum Ratings

Item	Symbol	Ratings	Unit	
Supply voltage	V _{CC}	7	V	
Input voltage	V _{IN}	7	V	
Power dissipation	PT	400	mW	
Storage temperature	Tstg	-65 to +150	°C	

Note: Voltage value, unless otherwise noted, are with respect to network ground terminal.



Recommended Operating Conditions

Item	Symbol	Min	Тур	Max	Unit
Supply voltage	V _{CC}	4.75	5.00	5.25	V
Output current	I _{OH}	—	—	-400	μA
Output current	I _{OL}	—	—	8	mA
Operating temperature	T _{opr}	-20	25	75	°C
Clock frequency	f_{clock}	0	—	20	MHz
Clock pulse width	t _{w (CK)}	25	—	—	ns
Load pulse width	t _{w (Load)}	35	—	—	ns
Setup time	t _{su}	20	—	—	ns
Hold time	t _{h (data)}	3	—	—	ns
Enable time	t _{enable}	40			ns

Electrical Characteristics

(Ta = -20 to +75 °C)

lte	em	Symbol	min.	typ.*	max.	Unit	Condition		
Input voltage		VIH	2.0	-		V			
		VIL	-	-	0.8	V			
Output wells as		V _{он}	2.7			V	$\label{eq:Vcc} \begin{split} V_{CC} &= 4.75 \text{ V}, \ V_{IH} = 2 \text{ V}, \ V_{IL} = 0.8 \text{ V}, \\ I_{OH} &= -400 \ \mu \text{A} \end{split}$		
Output vol	laye	V _{OL}			0.4	V	$I_{OL} = 4 \text{ mA}$ $V_{CC} = 4.75 \text{ V}, \text{ V}_{IH} = 2 \text{ V},$		
		V OL			0.5	v	$I_{OL} = 8 \text{ mA}$ $V_{IL} = 0.8 \text{ V}$		
	Enable	- I _{IH}			60		$V_{CC} = 5.25 \text{ V}, \text{ V}_1 = 2.7 \text{ V}$		
	Others		-	(20	μΑ	$v_{CC} = 5.25 v, v_1 = 2.7 v$		
Input	Enable	- I _{IL}	-	-	-1.2	mA	$V_{CC} = 5.25 \text{ V}, \text{ V}_{I} = 0.4 \text{ V}$		
current	Others		-		-0.4		$v_{CC} = 5.25 \ v, \ v_{I} = 0.4 \ v$		
	Enable	- I _l	-		0.3	mA	$V_{CC} = 5.25 \text{ V}, \text{ V}_{I} = 7 \text{ V}$		
	Others			—	0.1	III/A	$v_{CC} = 5.25 v, v_{I} = 7 v$		
Short-circu current	iit output	los	-20	-0	-100	mA	V _{CC} = 5.25 V		
Supply current**		Icc	<u> </u>	20	35	mA	V _{CC} = 5.25 V		
Input clamp voltage		VIK	—	-	-1.5	V	$V_{CC} = 4.75 \text{ V}, I_{IN} = -18 \text{ mA}$		

Notes: $* V_{CC} = 5 V$, Ta = 25°C

** Icc is measured with all outputs open and all inputs grounded.



Switching Characteristics

 $(V_{CC} = 5 V, Ta = 25^{\circ}C)$

Item	Symbol	Inputs	Outputs	min.	typ.	max.	Unit	Condition
Maximum clock frequency	$f_{\sf max}$	Clock	Q _A , Q _B , Q _C , Q _D	20	25	_	MHz	
	t _{PLH}	Load Q _A , Q _B ,	Q_A, Q_B, Q_C, Q_D		22	33	ns	C _L = 15 pF, R _L = 2 kΩ
	t _{PHL}		$\mathbf{Q}_{A}, \mathbf{Q}_{B}, \mathbf{Q}_{C}, \mathbf{Q}_{D}$		33	50		
	t _{PLH}	А, В,	Q _A , Q _B , Q _C , Q _D		20	32	ns	
	t _{PHL}	C, D	$\mathbf{Q}_{A}, \mathbf{Q}_{B}, \mathbf{Q}_{C}, \mathbf{Q}_{D}$		27	40		
	t _{PLH}	Cleak	Ripple Clock		13	20	ns	
	t _{PHL}	Clock			16	24		
Propagation delay time	t _{PLH}	Clock	0 0 0		16	24	ns	
	t _{PHL}	CIUCK	Q_A, Q_B, Q_C, Q_D		24	36		
	t _{PLH}	Clock	Max / Min		28	42	ns	
	t _{PHL}	CIUCK			37	52		
	t _{PLH}	Down /	Ripple Clock		30	45	ns	
	t _{PHL}	Up			30	45		
	t _{PLH}	Down /	Max / Min		21	33	ns	
	t _{PHL}	Up		_	22	33		
	t _{PLH}	Enable	Pipple Cleck	_	21	33	00	
	t _{PHL}	LIADIE	Ripple Clock	_	22	33	ns	



Count Sequences





Testing Method

Test Circuit



Waveforms 1



HD74LS190

Waveforms 2



Waveforms 3



Rev.3.00, Jul.15.2005, page 8 of 10

Waveforms 4



2. When test the Q_D output, data inputs A and D are shown by the solid line, and data inputs B and C are held at the low logic level.







Package Dimensions





Renesas Technology Corp. sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs! 1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

- Notes regarding these materials
 These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
 Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or oricruit application examples contained in these materials.
 All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. virbuut notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information described here may contain technical inaccuracies or typographical errors. Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (http://www.renesas.com).
 When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, or errors.

- Nome page (ntp://www.renesas.com).
 4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
 5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- use. 6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials. 7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited. 8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



http://www.renesas.com

RENESAS SALES OFFICES

Refer to "http://www.renesas.com/en/network" for the latest and detailed information.

Renesas Technology America, Inc. 450 Holger Way, San Jose, CA 95134-1368, U.S.A Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K. Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology Hong Kong Ltd. 7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd. 10th Floor, No.99, Fushing North Road, Taipei, Taiwan Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd. Unit2607 Ruijing Building, No.205 Maoming Road (S), Shanghai 200020, China Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.

1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632 Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd. Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea Tel: <82> 2-796-3115, Fax: <82> 2-796-2145

Renesas Technology Malaysia Sdn. Bhd.

Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jalan Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia Tel: <603> 7955-9390, Fax: <603> 7955-9510