

HD74LS245

Octal Bus Transceivers (with three-state outputs)

REJ03D0464-0300 Rev.3.00 Jul.15.2005

This octal bus transceiver is designed for synchronous two-way communication between data buses. The control function implementation minimizes external timing requirements. The device allows data transmission from the A bus to the B bus or from the B bus to the A bus depending upon the logic level at the direction control (DIR) input. The enable input (\overline{G}) can be used to disable the device so that the buses are effectively isolated.


Features

• Ordering Information

Part Name	Package Type	Package Code (Previous Code)	Package Abbreviation	Taping Abbreviation (Quantity)
HD74LS245P	DILP-20 pin	PRDP0020AC-B (DP-20NEV)	Р	_
HD74LS245FPEL	SOP-20 pin (JEITA)	PRSP0020DD-B (FP-20DAV)	FP	EL (2,000 pcs/reel)
HD74LS245RPEL	SOP-20 pin (JEDEC)	PRSP0020DC-A (FP-20DBV)	RP	EL (1,000 pcs/reel)

Note: Please consult the sales office for the above package availability.

Pin Arrangement




Function Table

Enable \overline{G}	Direction Control DIR	Operation	
L	L	B data to A bus	
L	Н	A data to B bus	
Н	X	Isolation	

Note: H; high level, L; low level, X; irrelevant

Block Diagram



Absolute Maximum Ratings

Item		Symbol	Ratings	Unit
Supply voltage		V _{CC}	7	V
Input voltage	DIR, G	V _{IN}	7	V
Input voltage	A, B	V _{IN}	5.5	V
Power dissipation		P _T	400	mW
Storage temperature		Tstg	-65 to +150	°C
Operating temperature		Topr	-20 to +75	°C

Note: Voltage value, unless otherwise noted, are with respect to network ground terminal.

Recommended Operating Conditions

Item	Symbol	Min	Тур	Max	Unit
Supply voltage	V _{CC}	4.75	5.00	5.25	V
Output current	I _{OH}	_	_	-15	mA
Output current	I _{OL}	_	_	24	mA
Operating temperature	Topr	-20	25	75	°C

Electrical Characteristics

 $(Ta = -20 \text{ to } +75 \text{ }^{\circ}\text{C})$

Ite	em	Symbol	min.	typ.*	max.	Unit	Condition		
Input voltage		V_{IH}	2.0			V			
Input voltag	le.	V_{IL}	_	_	0.8	V			
Hysteresis		$V_T^+ - V_T^-$	0.2	0.4		V	V _{CC} = 4.75 V		
		V_{OH}	2.4			٧	$I_{OH} = -3 \text{ mA}$	$V_{CC} = 4.75 \text{ V}, V_{IH} = 2 \text{ V},$	
Output volt	200	VOH	2				$I_{OH} = -15 \text{ mA}$	$V_{IL} = 0.8 V$	
Output volta	age	V	_	_	0.4	V	I _{OL} = 12 mA	$V_{CC} = 4.75 \text{ V}, V_{IH} = 2 \text{ V},$	
		V_{OL}	_	_	0.5	V	I _{OL} = 24 mA	$V_{IL} = 0.8 V$	
Off state or	Off-state output current		_	_	20		V _O = 2.7 V	$V_{CC} = 5.25 \text{ V}, \overline{G} = 2 \text{ V}$	
OII-State of	ilpul current	I _{OZL}	_	_	-200	μΑ	V _O = 0.4 V	v _{CC} = 5.25 v, G = 2 v	
			_	_	20	μΑ	$V_{CC} = 5.25 \text{ V}, V_I = 2.7 \text{ V}$		
Input		I _{IL}	_	_	-0.2	mA	$V_{CC} = 5.25 \text{ V}, V_{I} = 0.4 \text{ V}$ $V_{CC} = 5.25 \text{ V}, V_{I} = 5.5 \text{ V}$		
current	A or B		_	_	0.1	mA			
	DIR or G	II	_	_	0.1	IIIA	V _{CC} = 5.25 V, V _I = 7 V		
Short-circuit output current		Ios	-40	_	-225	mA	V _{CC} = 5.25 V		
Supply current**		Іссн	_	48	70				
		I _{CCL}	_	62	90	mA $V_{CC} = 5.25 \text{ V}$			
		I _{CCZ}	_	64	95				
Input clamp voltage		V _{IK}	_	_	-1.5	V	$V_{CC} = 4.75 \text{ V}, I_{IN}$	_I = –18 mA	

Notes: $V_{CC} = 5 \text{ V}$, $Ta = 25^{\circ}\text{C}$

Switching Characteristics


 $(V_{CC} = 5 \text{ V}, \text{Ta} = 25^{\circ}\text{C})$


Item	Symbol	min.	typ.	max.	Unit	Condition	
Dranagation dalay time	t _{PLH}		8	15			
Propagation delay time	t _{PHL}		11	15		$C_L = 45 \text{ pF}, R_L = 667 \Omega$	
Output anabla tima	t _{ZL}		27	40	ns		
Output enable time	t _{ZH}		25	40			
Output disable time	t_{LZ}		15	25		$C_L = 5 \text{ pF}, R_L = 667 \Omega$	
Output disable tillle	t _{HZ}	_	15	25		$C_L = 3 \text{ pr}, K_L = 667 \Omega$	


Note: Refer to Test Circuit and Waveform of the Common Item "TTL Common Matter (Document No.: REJ27D0005-0100)".

^{**} With all outputs open, I_{CC} is measured with transceivers enabled in one direction only, or with all transceivers disabled.

Package Dimensions







Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!

1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.

Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

Notes regarding these materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.

2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.

The information described here may contain technical inaccuracies or typographical errors.

Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.

Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (http://www.renesas.com).

- A. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

 5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.

use.

6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.

7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.

Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.

8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



RENESAS SALES OFFICES

http://www.renesas.com

Refer to "http://www.renesas.com/en/network" for the latest and detailed information.

Renesas Technology America, Inc. 450 Holger Way, San Jose, CA 95134-1368, U.S.A Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology Hong Kong Ltd.
7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd. 10th Floor, No.99, Fushing North Road, Taipei, Taiwan Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd. Unit2607 Ruijing Building, No.205 Maoming Road (S), Shanghai 200020, China Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.

1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632 Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd.Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea Tel: <82> 2-796-3115, Fax: <82> 2-796-2145

Renesas Technology Malaysia Sdn. Bhd. Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jalan Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia Tel: <603> 7955-9390, Fax: <603> 7955-9510

l		