- Contain Six Flip-Flops With Single-Rail Outputs
- Applications Include:
 - Buffer/Storage Registers
 - Shift Registers
 - Pattern Generators
- Package Options Include Plastic Small-Outline (D) and Ceramic Flat (W) Packages, Ceramic Chip Carriers (FK), and Standard Plastic (N) and Ceramic (J) 300-mil DIPs


description

These monolithic positive-edge-triggered D-type flip-flops have a direct clear (CLR) input.


Information at the data (D) inputs meeting the setup time requirements is transferred to the outputs on the positive-going edge of the clock (CLK) pulse. Clock triggering occurs at a particular voltage level and is not directly related to the transition time of the positive-going edge of CLK. When CLK is at either the high or low level, the D input has no effect at the output.

The SN54HC174 is characterized for operation over the full military temperature range of –55°C to 125°C. The SN74HC174 is characterized for operation from –40°C to 85°C.

SN54HC174 . . . J OR W PACKAGE SN74HC174 . . . D OR N PACKAGE (TOP VIEW)



SN54HC174 . . . FK PACKAGE (TOP VIEW)



NC - No internal connection

FUNCTION TABLE (each flip-flop)


	INPUTS		OUTPUT
CLR	CLK	D	Q
L	Х	Χ	L
Н	\uparrow	Н	н
Н	\uparrow	L	L
Н	L	Χ	Q ₀



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.




logic symbol[†]



 $[\]ensuremath{^{\dagger}}$ This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12. Pin numbers shown are for the D, J, N, and W packages.

logic diagram (positive logic)



Pin numbers shown are for the D, J, N, and W packages.

absolute maximum ratings over operating free-air temperature range

Supply voltage range, V _{CC}	–0.5 V to 7 V
Input clamp current, I_{IK} ($V_I < 0$ or $V_I > V_{CC}$) (see Note 1)	±20 mA
Output clamp current, I _{OK} (V _O < 0 or V _O > V _{CC}) (see Note 1)	±20 mA
Continuous output current, I_O ($V_O = 0$ to V_{CC})	±25 mA
Continuous current through V _{CC} or GND	±50 mA
Package thermal impedance, θ _{JA} (see Note 2): D package	113°C/W
N package	78°C/W
Storage temperature range, T _{sto}	65°C to 150°C

^{\$} Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- NOTES: 1. The input and output voltage ratings may be exceeded if the input and output current ratings are observed.
 - 2. The package thermal impedance is calculated in accordance with JESD 51, except for through-hole packages, which use a trace length of zero.



recommended operating conditions

			NS	SN54HC174			SN74HC174		
			MIN	NOM	MAX	MIN	NOM	MAX	UNIT
Vcc	Supply voltage		2	5	6	2	5	6	V
		V _{CC} = 2 V	1.5			1.5			
ViH	High-level input voltage	V _{CC} = 4.5 V	3.15			3.15			V
		V _{CC} = 6 V	4.2			4.2			
	Low-level input voltage	V _{CC} = 2 V	0		0.5	0		0.5	
VIL		V _{CC} = 4.5 V	0		1.35	0		1.35	V
		V _{CC} = 6 V	0		1.8	0		1.8	
VI	Input voltage		0		VCC	0		VCC	V
Vo	Output voltage		0		VCC	0		VCC	V
	Input transition (rise and fall) time	V _{CC} = 2 V	0		1000	0		1000	
t _t		$V_{CC} = 4.5 \text{ V}$	0		500	0		500	ns
		V _{CC} = 6 V	0		400	0		400	
TA	Operating free-air temperature	-	-55		125	-40		85	°C

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

DADAMETER	TEST CONDITIONS		V	Т	A = 25°C	;	SN54HC174		SN74HC174		LINIT	
PARAMETER	1551 CC	SNOTTIONS	vcc	MIN	TYP	MAX	MIN	MAX	MIN	MAX	UNIT	
			2 V	1.9	1.998		1.9		1.9			
		I _{OH} = -20 μA	4.5 V	4.4	4.499		4.4		4.4			
Voн	VI = VIH or VIL		6 V	5.9	5.999		5.9		5.9		٧	
		$I_{OH} = -4 \text{ mA}$	4.5 V	3.98	4.3		3.7		3.84			
		$I_{OH} = -5.2 \text{ mA}$	6 V	5.48	5.8		5.2		5.34			
	VI = VIH or VIL	I _{OL} = 20 μA	2 V		0.002	0.1		0.1		0.1		
			4.5 V		0.001	0.1		0.1		0.1		
VOL			6 V		0.001	0.1		0.1		0.1	V	
		I _{OL} = 4 mA	4.5 V		0.17	0.26		0.4		0.33		
				$I_{OL} = 5.2 \text{ mA}$	6 V		0.15	0.26		0.4		0.33
lį	$V_I = V_{CC}$ or 0		6 V		±0.1	±100		±1000		±1000	nA	
Icc	$V_I = V_{CC}$ or 0,	I _O = 0	6 V			8		160		80	μΑ	
C _i			2 V to 6 V		3	10		10		10	pF	

timing requirements over recommended operating free-air temperature range (unless otherwise noted)

			V	T _A =	25°C	SN54F	IC174	SN74H	IC174	UNIT
			VCC	MIN	MAX	MIN	MAX	MIN	MAX	ONT
	f _{clock} Clock frequency		2 V	0	6	0	4.2	0	5	
fclock			4.5 V	0	31	0	21	0	25	MHz
			6 V	0	36	0	25	0	29	
			2 V	80		120		100		
t _W Pulse duration	CLR low	4.5 V	16		24		20			
	Pulso duration		6 V	14		20		17		ns
	ruise duration	CLK high or low	2 V	80		120		100		
			4.5 V	16		24		20		
			6 V	14		20		17		
		Data	2 V	100		150		125		ns
			4.5 V	20		30		25		
١.	Setup time before CLK↑		6 V	17		25		21		
t _{su}	Setup time before CENT		2 V	100		150		125		
		CLR inactive	4.5 V	20		30		25		
			6 V	17		25		21		
			2 V	0		0		0	, and the second	
th	Hold time, data after CLK↑		4.5 V	0		0		0		ns
			6 V	0		0	·	0		

switching characteristics over recommended operating free-air temperature range, C_L = 50 pF (unless otherwise noted) (see Figure 1)


PARAMETER	FROM	TO (OUTPUT)	Vaa	T,	ղ = 25°C	;	SN54H	C174	SN74H	IC174	UNIT
PARAMETER	(INPUT)		VCC	MIN	TYP	MAX	MIN	MAX	MIN	MAX	UNIT
			2 V	6	9		4.2		5		
f _{max}			4.5 V	31	44		21		25		MHz
			6 V	36	50		25		29		
			2 V		58	160		240		200	
	CLR	Any	4.5 V		17	32		48		40	
. .			6 V		14	27		41		34	ns
^t pd	CLK	Any	2 V		58	160		240		200	115
			4.5 V		17	32		48		40	
			6 V		14	27		41		34	
t _t		Any	2 V		38	75		110		90	
			4.5 V		8	15		22		19	ns
			6 V		6	13		19		16	

operating characteristics, $T_A = 25^{\circ}C$

	PARAMETER	TEST CONDITIONS	TYP	UNIT
C _{pd}	Power dissipation capacitance per flip-flop	No load	27	pF



PARAMETER MEASUREMENT INFORMATION



NOTES: A. C_L includes probe and test-fixture capacitance.

- B. Phase relationships between waveforms were chosen arbitrarily. All input pulses are supplied by generators having the following characteristics: PRR \leq 1 MHz, $Z_O = 50 \ \Omega$, $t_\Gamma = 6 \ ns$, $t_f = 6 \ ns$.
- C. For clock inputs, $f_{\mbox{max}}$ is measured when the input duty cycle is 50%.
- D. The outputs are measured one at a time with one input transition per measurement.
- E. tpLH and tpHL are the same as tpd.

Figure 1. Load Circuit and Voltage Waveforms

IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgement, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

CERTAIN APPLICATIONS USING SEMICONDUCTOR PRODUCTS MAY INVOLVE POTENTIAL RISKS OF DEATH, PERSONAL INJURY, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE ("CRITICAL APPLICATIONS"). TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF TI PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE FULLY AT THE CUSTOMER'S RISK.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.

Copyright © 1998, Texas Instruments Incorporated