

- 3-Terminal Regulators
- Output Current up to 100 mA
- No External Components
- Internal Thermal-Overload Protection
- Internal Short-Circuit Current Limiting
- Provided Pb-Free packages from the end of 2004

#### description

This series of fixed-voltage integrated-circuit voltage regulators is designed for a wide range of applications. These applications include on-card regulation for elimination of noise and distribution problems associated with single-point regulation. In addition, they can be used with power-pass elements to make high-current voltage regulators. One of these regulators can deliver up to 100 mA of output current. The internal limiting and thermal-shutdown features of these regulators make them essentially immune to overload. When used as a replacement for a zener diode-resistor combination, an effective improvement in output impedance can be obtained, together with lower bias current.



PARAMETER	TEST CONDITIONS	т‡	78L24			UNIT	
			MIN	ТҮР	MAX	1	
Output voltage		25°C	23	24	25	v	
	$I_0 = 1$ mA to 40MA, $V_1 = 26.5$ to 39V	Full range	22.8	24	25.2		
	$I_0 = 1 \text{ mA to } 70 \text{ mA}$	Full range	22.8	24	25.2		
Input voltage regulation	V <sub>I</sub> = 26.5V to 39V	25 <sup>°</sup> C		95	480	mV	
	V <sub>1</sub> = 29V to 39V			78	400		
Ripple rejection	V <sub>I</sub> =27.5V to 37.5V, f = 120 Hz	25°C	30	33		dB	
Output voltage regulation	I <sub>O</sub> = 1 mA to 100 mA	25°C		41	240	mV	
	$I_{O} = 1 \text{ mA to } 40 \text{ mA}$			28	120		
Output noise voltage	f = 10 Hz to 100 kHz	25°C		97		μV	
Dropout voltage		25°C		1.7		V	
Bias current		25°C		4.8	6.5	mA	
		125°C			6		
Bias current change	V <sub>I</sub> = 28V to 39V	Full range			1.5		
	$I_{O} = 1 \text{ mA to } 40 \text{ mA}$				0.1	mA	

# electrical characteristics at specified virtual junction temperature, $V_I = 32V$ , $I_o = 40mA$ (unless otherwise noted)

<sup>‡</sup> Pulse-testing techniques maintain T<sub>J</sub> as close to T<sub>A</sub> as possible. Thermal effects must be taken into account separately. All characteristics are measured with a 0.33-μF capacitor across the input and a 0.1-μF capacitor across the output. Full range for the 78L05 is T<sub>J</sub> = 0°C to 70°C

## **Positive-Voltage Regulators**

#### absolute maximum ratings over operating temperature range (unless othewise noted)

78L24		UNIT
Input voltage, VI	40	V
Virtual junction temperature range, TJ		°C
Lead temperature 1,6 mm (1/16 inch) from case for 10 seconds		°C
Storage temperature range, T <sub>Stg</sub>		°C

## recommended operating conditions

78L24	MIN	MAX	UNIT
Input voltage, VI	26.5	39	V
Output current, I <sub>O</sub>		100	mA
Operating virtual junction temperature, TJ		70	°C

## Pad Location 78L24



#### Chip size 1.0 x 1.2 mm

Pad N	Pad Name	X (um)	Y (um)
1	Ground	95	100
2	Input	820	1010
3	Output	535	1015